

# 3 loop fire alarms

## Data sheet

AATS4081 - AATS4082

---

### Technical Department

Tél. : +33 (0) 160 215 125  
Fax : +33 (0) 160 215 128  
E-mail : [technique@cordia.fr](mailto:technique@cordia.fr)

### Sales Department

Tel: +33 (0) 160 215 130  
Fax: +33 (0) 160 215 139  
E-mail: [contact@cordia-fire-safety.com](mailto:contact@cordia-fire-safety.com)

---

[www.myfiresafetyproducts.com](http://www.myfiresafetyproducts.com)

---



AATS4081



AATS4082



- Mains powered.
- 3 loops.
- Beacon.

---

## Applications

All buildings except if automatic detectors required.

---

## Associated products

- Manual callpoint (ADMR8001).
- Sounder (ADIS0013).
- Sounder beacon (ADSV0013).
- Industrial sounder beacon (TDSV0001).
- External power supply (AALS2425).

# 3 loop fire alarms

## Data sheet

AATS4081 - AATS4082

### Technical Department

Tél. : +33 (0) 160 215 125  
Fax : +33 (0) 160 215 128  
E-mail : [technique@cordia.fr](mailto:technique@cordia.fr)

### Sales Department

Tel: +33 (0) 160 215 130  
Fax: +33 (0) 160 215 139  
E-mail: [contact@cordia-fire-safety.com](mailto:contact@cordia-fire-safety.com)

[www.myfiresafetyproducts.com](http://www.myfiresafetyproducts.com)



AATS4081



AATS4082

## Technical characteristics

<b>Power supply</b>	230 V / 50 Hz
<b>Secondary power supply</b>	3 batteries 1.2 V Ni/MH 2000 mAh
<b>Number of manual callpoint loops</b>	3
<b>Max. number of manual callpoints per loop</b>	32
<b>Sounder output</b>	16 V / 200 mA maximum
<b>IP rating</b>	IP 30
<b>Flashing light</b>	4 LEDs, 6 candelas
<b>Auxiliary relay</b>	1 NO/NC (24 V / 1 A)
<b>Fault relay</b>	1 NO/NC (24 V / 1 A)

<b>Part number</b>	AATS4081	AATS4082
<b>Manual callpoint</b>	-	Resettable, with hinged cover
<b>Evacuation signal</b>	-	Sound + flash
<b>Tone*</b>	-	English
<b>Weight</b>	800 g	900 g
<b>Dimensions</b>	W.180 x H.275 x D.55 mm	W.180 x H.275 x D.55 mm

\*Other tones available on request.